



3W EMERGENCY LIGHT

- Injection- molded ABS plastic housing
- Innovative, easy installation in minutes
- Test switch/LED charge indicator provided
- Suitable for damp locations
- Overcharge and over-discharge protection

Rated voltage: 100-227V, 60Hz

Rated power: 3W

Emergency time: 3hrs

Emergency power: 2x1.6W

Emergency switch time: $\leq 0.25s$

Emergency output flux: 120lm

Battery: Nickel Cadmium Battery 3.6V 1000mAh

Charging time: $\leq 24h$

Ingress protection: IP20

Operating Temperature: 0-40 Degrees Celsius